

APEX MICROTECHNOLOGY CORPORATION  
RELIABILITY PREDICTION  
PA84

by

Granger Scofield

Date of prediction: 15-Mar-01

This reliability prediction is based on MIL-HDBK-217F,  
December 2, 1991 including Notice 2, February 28, 1995.

Conditions of this prediction are as follows:

Hybrid quality level is		Commercial
Environment is	Gf	Ground, Fixed
Case temperature is		40 C
Internal Power Dissipation =		5 W
Supply voltage is +/-		120 V
An AC signal is applied.		
Product introduction date:		01-Aug-81

The results of this prediction are:

4.34 failures per million hours; or,  
MTBF=230.6 thousand hours.

## Transistors, Low Frequency, Bipolar:

$$L_p = L_b * P_{iT} * P_{iR} * P_{iS}$$

Q7		Volts = 40	Watts = 1.2	Tj = 175	'K/W= 125	
Usage:	Vstress = 1.3	Vpwr = 1.3	Ic = 1E-06	Vs = 0.0325	Power = 1E-06	
Lb	PiT	PiR	PiS	Nc	Tj = 40	
0.00074	1.404905	1.0698	0.04977	1		5.54E-05
Q11		Volts = 40	Watts = 1.2	Tj = 175	'K/W= 125	
Usage:	Vstress = 1.13	Vpwr = 1.13	Ic = 0.003	Vs = 0.0283	Power = 0.0034	
Lb	PiT	PiR	PiS	Nc	Tj = 40.424	
0.00074	1.417787	1.0698	0.049119	1		5.51E-05
Q6,17		Volts = 300	Watts = 26	Tj = 150	'K/W= 4.8077	
Usage:	Vstress = 235	Fraction Output Pwr = 1/	1	Vs = 0.7833	Power = 5	
Lb	PiT	PiR	PiS	Nc	Tj = 64.038	
0.00074	2.274314	3.3384	0.510298	2		0.005734
Q8,9		Volts = 300	Watts = 1.15	Tj = 150	'K/W= 108.7	
Usage:	Vstress = 110.3	Vpwr = 110.3	Ic = 0.0005	Vs = 0.3677	Power = 0.0552	
Lb	PiT	PiR	PiS	Nc	Tj = 45.995	
0.00074	1.595022	1.0531	0.140672	1		0.000175
Q15		Volts = 300	Watts = 1.15	Tj = 150	'K/W= 108.7	
Usage:	Vstress = 111.6	Vpwr = 111.6	Ic = 0.0012	Vs = 0.372	Power = 0.1295	
Lb	PiT	PiR	PiS	Nc	Tj = 54.071	
0.00074	1.87862	1.0531	0.142574	1		0.000209
Q3,16		Volts = 300	Watts = 1.15	Tj = 150	'K/W= 108.7	
Usage:	Vstress = 232.9	Vpwr = 118.3	Ic = 4E-09	Vs = 0.7763	Power = 5E-07	
Lb	PiT	PiR	PiS	Nc	Tj = 40	
0.00074	1.404902	1.0531	0.499344	2		0.001093
Q5		Volts = 300	Watts = 1.15	Tj = 150	'K/W= 108.7	
Usage:	Vstress = 110.2	Vpwr = 110.2	Ic = 0.0002	Vs = 0.3673	Power = 0.0176	
Lb	PiT	PiR	PiS	Nc	Tj = 41.917	
0.00074	1.46385	1.0531	0.140526	1		0.00016
Q1		Volts = 20	Watts = 0.38	Tj = 150	'K/W= 328.95	
Usage:	Vstress = 0.65	Vpwr = 0.65	Ic = 0.0005	Vs = 0.0325	Power = 0.0003	
Lb	PiT	PiR	PiS	Nc	Tj = 40.107	
0.00074	1.408144	0.6991	0.04977	1		3.63E-05

Q2,4		Volts = 20	Watts = 0.38	Tj = 150	'K/W= 328.95
Usage:	Vstress = 3	Vpwr = 1.55	Ic = 0.0005	Vs = 0.15	Power = 0.0008
Lb	PiT	PiR	PiS	Nc	Tj = 40.255
0.00074	1.412643	0.6991	0.071641	2	0.000105

Transistors, Low Frequency, Si JFET: Lb = 0.0045  
Lp = Lb \* PiT

Q12		Volts = 50	Watts = 4	Tj = 150	'K/W= 31.25
Usage:		Vpwr = 5.4	Id = 0.0005		Power = 0.0027
Lb	PiT			Nc	Tj = 40.084
0.0045	1.365102			2	0.012286

Q13,14		Volts = 30	Watts = 0.8	Tj = 150	'K/W= 156.25
Usage:		Vpwr = 5.03	Id = 2E-09		Power = 1E-08
Lb	PiT			Nc	Tj = 40
0.0045	1.362841			2	0.012266

Q10		Volts = 300	Watts = 3	Tj = 150	'K/W= 41.667
Usage:		Vpwr = 231.6	Id = 0.0014		Power = 0.3312
Lb	PiT			Nc	Tj = 53.8
0.0045	1.766976			1	0.007951

Capacitors, ceramic general purpose type CK:  
Lp = Lb \* PiT \* PiC \* PiV Lb = 0.00099

C2		Volts = 100	pF = 1000	S = 0.01	
Usage:	Vstress = 1				
Lb	PiT	PiC	Pi V	Nc	
0.00099	1.92167	0.288	1	1	0.000549

C5,6		Volts = 200	pF = 100	S = 0.005	
Usage:	Vstress = 1				
Lb	PiT	PiC	Pi V	Nc	
0.00099	1.92167	0.234	1	2	0.000892

C4		Volts = 200	pF = 150	S = 0.032	
Usage:	Vstress = 6.4				
Lb	PiT	PiC	Pi V	Nc	
0.00099	1.92167	0.243	1.0002	1	0.000463

C1		Volts = 45	pF = 47	S = 0.0233	
Usage:	Vstress = 1.05				
Lb	PiT	PiC	Pi V	Nc	
0.00099	1.92167	0.219	1.0001	1	0.000417

Diodes, Low Frequency:

$$L_p = L_b * P_{iT} * P_{iS} * P_{iC}$$

Diodes, Zener,  $L_b = 0.002$

D1			Volts = 3.1	Watts = 2.5	Tj = 175	'K/W= 60	
Usage:				lc = 0.001		Power = 0.0031	
Lb	PiT	PiS	PiC		Nc	Tj = 40.186	
0.002	1.367828	1	2		1		0.005471

D2			Volts = 3.1	Watts = 2.5	Tj = 175	'K/W= 60	
Usage:				lc = 0.0014		Power = 0.0044	
Lb	PiT	PiS	PiC		Nc	Tj = 40.266	
0.002	1.369977	1	2		1		0.00548

Sum of all components 0.053397

Hybrid microcircuit:

$$L_p = \text{sum} L_c * (1 + 2 * P_{iE}) * P_{iF} * P_{iQ} * P_{iL}$$

0.053397 1.4 5.8 10 1

Total failures per million hours = 4.335837

Mean time between failures = 230636